

inCloud - Basic Features


SOURCE:

<https://support.zortrax.com/incloud-basic-features/>

Table Of Contents

Dashboard
Multiprint
Statistics
Timeline
Teams
Shelves
All Prints
Multistream
Printer details
Settings

Dashboard




Dashboard is the main panel where you can start all your Zortrax inCloud activities and easily find all necessary functionalities. You can add a device you have registered on your ID account with the *Add device* button in the top right corner of the page. In the pop-up window, click *Add device* next to the selected device you want to add to inCloud.

All added printers will appear on the *Unassigned* list. You can arrange those devices in one or more groups, and change the name of the group you have created. At the top of the page, there is information about your current subscription plan and available transfer.


The *Find device* option allows you to quickly determine a device's location. Click on the location pin next to the device you want to locate. Next, you will receive a notification whether the device has entered the location mode. If device location is possible, special animation will flash on the printer's screen which will help you quickly find the device you're looking for.

Multiprint




The **Multiprint** makes it easier to run 3D printing farms as it lets you print the same model with all your 3D printers. This solution is targeted at mass production processes. As you upload a model, the printing process is initiated on the selected devices at the same time. Simply choose a file and select the printers you want to use to begin the production.

Statistics



The **Statistics** tab gathers various data related to devices and users. You can choose the date range for the stats you want to preview. Statistics include total printing time with all added devices, most used 3D printers, total amount of used materials, as well as printers which require maintenance or firmware update. There is also information about transfer used up by each printer and user. Admins have access to data from the entire Organization and all other users, including data on users' printing time and material usage.

Timeline



Timeline shows all activities connected to each added printer. There you can see which printer is currently working, which is idle at the moment, which part of the project is currently being completed, and which users have been involved in the process. It is possible to see all models printed with each device. Move the mouse over the selected field to display more details related to the printer's work. You can easily scroll through the whole timeline of a printer.

Teams

The **Teams** tab supports teamwork among people employed in one company or involved in the same project. If you want to cooperate with other people, you can create a team and share the added printers with authorized users. Your teammates will be able to manage and print with the shared devices from their own individual accounts. It is possible to move users from one team to another, and dynamically reassign the available devices. Remember that each printer can have only one administrator who can control all the work at any point during the project.

There are two options that allow users to share devices with others. With the *Share device* option you can select a Team and a user who will receive access to a printer. The *Copy link* option lets you send a direct link to the selected device.

The screenshot shows the Zortrax INCLOUD interface. The top navigation bar includes the Zortrax logo, the text 'INCLOUD', and icons for a shopping cart, a notification bell, and a user profile. A left sidebar contains a menu with items: '+ Add device', 'Multiprint', 'My dashboard', 'Statistics', 'Timeline', 'Teams' (highlighted), 'Shelves', 'All prints', 'Multistream', 'Settings', 'ID Account', 'Feature/bug report', and 'Log out'. The main content area is titled 'Teams' and features a 'Create team' button with a help icon. Below this, a table lists three teams:

Team Name	Devices	Users	Action
Marketing	2	5	Manage
Sales	5	10	Details
Support	10	6	Details

- + Add device
- 🔄 Multiprint
- 📄 My dashboard
- 📊 Statistics
- 📅 Timeline
- 👤 Teams
- 🗄 Shelves
- 🌟 All prints
- 📁 Multistream
- ⚙ Settings
- 👤 ID Account
- ⚠ Feature/bug report
- 👉 Log out

< Teams | Marketing

Users list

Users

Possible number of users



[+Add more Users](#)

Add User Choose user

- Joe Doe
- Coby Squires
- Stefania Mpherson
- Diego Hurley
- Corrie Vasquez

Device list

Devices

Number of your 3D printers



[+Add more Devices](#)

Transfer

Amount of data transfer. Your plan will renew on 01 01 2021




[+Add more Transfer](#)

Add device Choose device

- Inkspire_1**
Zortrax Inkspire Ready to print
- Inkspire_2**
Zortrax Inkspire Offline

Shelves




The **Shelves** tab lets you arrange all added printers in such a way to match the exact setup in your print room. You can easily assign a place to each added device.

Open the *Shelves* tab and click the *Create shelf* in the top right corner of the window. In the pop-up window, enter the shelf's name, choose the number of columns and rows, and click *Add*.

Select the *Manage* option to open the Shelf. You can add a device in the selected place with the **+** button. Once you add a device, a miniature of the printer model will appear on the shelf, including its current status and information about the loaded material.


All Prints



In the **All Prints** tab, you can preview all printed models with detailed information. The list shows thumbnails of all models, file names, and the date of completion of the project. Administrators can preview all prints done in the entire Organization. Filters let you choose whose prints will be visible in the tab.


When you click on a model's thumbnail, you will be able to see all details regarding the print, including printing time and its outcome (Success/Failure). Additionally, each project can be evaluated with the star rating system.

Multistream




The **Multistream** tab allows you to collect and preview camera live streams from all your 3D printers that are currently connected to your account. This way, you get easy access to all your devices so as to supervise your projects from any place you want.

Printer details



Once you click your printer's name, you will be redirected to the **Printer details** tab. This is a space that aggregates all information related to the device, including the serial number and firmware version. Here you can upload files to the device's storage, create a new catalog for your files, and remotely start the printing process. There is also information about device logs and the whole print history. You can edit device's details, for example, change the name, assign it to a different group, or leave a note for your teammates with key information about the device or project.

Settings



This menu allows you to change the notification settings and download the newest firmware update for your device.

Adding a profile picture

Click on the icon with user's initials in the top right corner of the page. Click the camera symbol, and in the pop-up window, select a picture from your hard drive or add one using the drag&drop method.